

Ceiling lamp 3 arms, 1 rotating



120V / 60 Hz
3x60W incandescent

Suitable for indoor use only. Maximum ambient temperature 25°C.
Caution : The luminaire shall be always connected to the main ground conductor.

Installation has to be carried out by a qualified electrician. This lamp must be permanently wired into the electric system. Always shut off power to the circuit before starting installation work.

The main conductors coming from the ceiling into the housing must have a minimal length of 15cm/6inch between the ceiling plate and the electrical connection to the lamp.

Smooth wire : connect to the line
Ribbed wire : connect to the neutral
Yellow/Green wire : connect to the ground

Different materials require different types of fittings. Always choose screws and plugs that are specially suited to the material.

If the external flexible cable or cord of this luminaire is damaged, it must be exclusively replaced by the manufacturer to avoid any hazard.

Shut off power to the circuit before changing the bulb.

Instructions

Ceiling lamp 3 arms, 1 rotating



1. Unpack without using any cutter or scissor because of possible scratches. Release the packaging of reflectors without removing it completely. Remove the cable protective caps in red plastic from the tubes (if any).
2. Screw the screws into the thread to remove the plate of the lamp.
3. Put one or the 2 arms into the V of the base, pulling gently their electric cable out of the round base. Screw the little set screws into the V of the base to block the arms.
4. Screw the brass screw of the lower curved arm without tightening it otherwise painting could be damaged.
5. Locate the positioning of the round plate to the ceiling according to the lamp's position you prefer.
6. Fix the round plate to the ceiling. Different materials require different types of fittings. Always choose screws and plugs that are specially suited to the material.
7. At this stage, at least 2 operators are necessary. Before starting, turn off power at main circuit panel. One operator maintains the lamp, second operator screws the black cable then connects electrical wires.
8. Match the holes of the round housing in front of the screws. Then unscrew about 2mm of the set screws.
9. Remove completely the packaging.
10. Screw the hexagonal brass screw. Before moving the lower curved arm, the screw must not be tightened otherwise painting could be damaged.

